



WIREFLEX TECHNOLOGIES

SPYSMS PRO Edition User Guide

© 2011 Wireflex Technologies

Send comments about this document to: support@spyphonelove.com

Wireflex Technologies. All rights reserved.

This product or document is protected by copyright and distributed under licenses restricting its use, copying, distribution, and decompilation.

No part of this product or document may be reproduced in any form by any means without prior written authorization of Wireflex Technologies and its licensors, if any.

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.



Please Recycle

Content

INTRODUCTION	1
FEATURES	2
INSTALL AND UNINSTALL	3
SMS SPY COMMANDS	4
SUPPORT	7



Please Recycle

Chapter 1

Introduction

SPYSMS PRO edition is intent for users who have privilege to monitor others' mobile phone. **Please be aware that such behavior might be illegal in your country. We request you to check local laws before using this software.**

SPYSMS PRO edition can run on S60 2nd and 3rd edition series phones. The software starts automatically upon phone is powered on. It does not have any GUI (Graphics User Interface) or icon. You can control the software by sending SMS commands.

SPYSMS PRO edition has 3 work modes.

A. Forwarding mode.

In this mode SMS Anywhere forwards incoming and outgoing short messages to a pre-defined number.

B. Recording mode.

In this mode SMS Anywhere records incoming and outgoing short messages to a file on the phone (with UTF8 encoding). Size of the file is up to 512K bytes. The log file is in folder "\\system\\apps\\wireflex\\" on S60 2nd edition phone or "\\wireflex\\" on S60 3rd edition phone.

You can upload the file to a PC via Bluetooth. To achieve this, you need software like file explorer.

C. Forwarding and recording mode.

Combination of mode **A** and **B**.



Chapter 2

Features

- Forward and log incoming and outgoing SMS.
- No GUI or icon on phone menu.
- Hide SMS sending indicator (the up arrow icon).
- Hide forwarding message.
- Remote control.
- Starts automatically upon phone boot.
- No SMS delivery report.



Chapter 3

Install

SPYSMS is standard S60 software. Please refer to your phone manual on how to install software.

Uninstall

For S60 3rd edition phone, you can uninstall the software in App Manager.

For S60 2nd edition phone:

If you want to remove SPYSMS PRO forever, please send command "SAxxxxxxxx KILL".

If you want to reinstall, please first send command "SAxxxxxxxx BYE".



Chapter 4

SPYSMS Commands

To configure and control SPYSMS, you need to send some specific commands.

SPYSMS commands are formatted as the pattern below:

SA[password][*white space*][action][parameter]

[password] is password consists of 8 characters. Each character can be any letters, digits or symbols. The default password is **12345678**. You can change the password. Commands with incorrect password can not take into effect.

[*white space*] is a white space character.

[action] and [parameter] are used to configure the software features. The following table shows all supported actions and parameters.

Action	Parameter	Behavior
ON	N/A	Turn on SPYSMS service. (default)
OFF	N/A	Turn off SPYSMS service.
P	[password]	Change password. The parameter is new password. A password must consist of 8 characters. (default: 12345678)
S	0	Do not forward outgoing messages. (default)
	1	Forward outgoing messages.
R	0	Do not forward incoming messages.
	1	Forward incoming messages. (default)
D	[phone number]	Set forward number. The parameter is forward phone number. Length of the number can be up to 20 characters.
L	[license code]	Install the commercial license code. (S60 2 nd edition only)
I	0	Do not delete original incoming messages. (default)



	1	Delete original incoming message after it got forwarded.
N	0	Do not delete original outgoing messages. (default)
	1	Delete original outgoing message after it got forwarded.
W	0	Set work mode to MODE A. (default)
	1	Set work mode to MODE B.
	2	Set work mode to MODE C.
E	0	Set message encoding to UNICODE. (default)
	1	Set message encoding to GSM7Bits.
	2	Set message encoding to 8Bits.
#	[phone number]	Set a specific number you want to monitor. After you set it, the software will only care messages from/to this specific number. To remove the specific number, please send the command again with no number. By default the software monitor all incoming and outgoing messages.
*	[phone number]	Set a black number which you do not want to monitor. After you set it, the software will NOT care messages from/to this black number. To remove the black number, please send the command again with no number.
H	N/A	Refresh the SMS log file – delete old log and write new log from file head.
BYE	N/A	Temporarily stop the software till next time phone is switched on. (S60 2 nd edition only)
KILL	N/A	Remove SPYSMS PRO from the phone. You might not able to install SPYSMS on the phone again. (S60 2 nd edition only)

Some command examples (assume password is **12345678**):

- To change the password to "abcdefgh", you should send command:

SA12345678 Pabcdefgh

- To set the destination phone number to +448888888888, you should send command:

SA12345678 D+448888888888



- To monitor messages from/to a specific number (5555555), you should send command:

SA12345678 #5555555

- To turn off the SPYSMS service, you should send command:

SA12345678 OFF

NOTE:

SPY SMS command is deleted from inbox automatically. No "New SMS Received" prompts displayed on the phone.

To upload SMS log via FTP, your FTP server should supports PASV mode. If you set up the FTP server on your PC, please make sure there is no firewall or other software block the connection. There is no guarantee SPYSMS can work with all FTP servers.

The default configuration for SPYSMS is as below:

- ◆ Default password is 12345678.
- ◆ The service is ON.
- ◆ Forward phone number is empty. (You must set a forward number after install.)
- ◆ Forward incoming SMS.
- ◆ Do not forward outgoing SMS.
- ◆ Do not delete original incoming and outgoing SMS.
- ◆ Default work mode is mode A.
- ◆ Default SMS encoding is UNICODE.
- ◆ Monitor all incoming SMS. (No specific or black number defined.)



Chapter 5

Support

If you have any questions or suggestions for us, please contact us:

Email : support@spyphonelove.com

Website : www.spyphonelove.com